ANG<mark>SEMI</mark>

LDO ICs

Micro-power Consumption, 600mA, Low Input Voltage, High PSRR Low-Dropout Voltage Linear Regulator

General Description

The AS9116 is a CMOS low dropout, low noise, low power consumption, high PSRR, low quiescent current positive linear regulator with input voltage down to about 1.20V. The AS9116 can deliver a guaranteed 600mA load current with a low dropout voltage that optimized for battery-powered systems or portable wireless devices such as mobile phones. Quiescent current of only 1.5uA makes these devices ideal for powering the battery-powered, always-on systems that require very little idle-state power dissipation to a longer service life. There is an option of shutdown function by selecting the parts with the EN pin and pulling it low. The off state of AS9116 that consumes less than 0.1uA during shutdown mode.

The device is suitable for portable application such as cellular handsets or PDA. The AS9116 is designed and optimized to work with low cost ceramic capacitors 1.0uF, which consumes less than 0.1µA during shutdown mode. Besides, its current limit protection and on-chip thermal shutdown function provide protection against any combination of over-load or ambient temperature which could cause junction temperature exceeding maximum rating. The AS9116 includes a reference bypass pin in order to reduce output noise and a logic control shut-down input.

The space-saving tiny SOT23-3L, SOT23-5L and DFN1010-4L packages are attractive for hand-held applications. The device is specified over an ambient temperature range of -40°C to 125°C.

Features

- Output Current Up to 600mA
- Low Voltage V_{IN} Range: 1.20V to 5.5V
- Very Low Input Voltage at 1.20V (Min.)
- Very Low Quiescent Current at 1.5uA
- Low Dropout voltage of 350mV at 600mA
- Output Voltage Accuracy at ±2.0%
- PSRR 75dB at 1.0KHz
- Needs Only 1.0uF Capacitor for Stability
- Current Limit Protection
- Current Fold-back Protection
- 0.01uA Shutdown Current
- Without EMI and Switch Noise
- Low ESR Ceramic Capacitor for Output Stability
- RoHS and Green Compliant
- DFN1010-4L, SOT23-3L and SOT23-5L Packages
- -40°C to +125 °C Temperature Range

Applications

- Portable, Battery Powered Equipment
- Low Power Microcontrollers
- PDAs and Digital Camera
- Wireless Communication Equipment
- Mobil Handsets
- Tablet PCs and Laptops/Netbooks
- Camcorder Video Light (Movie Light)
- Audio/Video Equipment

www.angsemi.com ANGSemi Microelectronics Co., Ltd. All rights reserved.



AS9116

Datasheet




• Ordering Information


	AS	9116XXXX	
Output Voltage: 08: 0.8V 09: 0.9V 12:1.2V 15:1.5V 18:1.8V 25:2.5V 28: 2.8V 30:3.0V 33: 3.3V	Package: D:DFN1010-4L S3: SOT23-3L S5: SOT23-5L	Packing: R:Tape&Reel	Temperature Grade: N: -40°C~85°C Y: -40°C~125°C

Part Number	Driver Capability	Package Type	Package Qty	Temperature	Eco Plan
AS9116-XXDRN	600mA	DFN1010-4L	7-in reel 10000pcs/reel	-40∼85 ℃	RoHS
AS9116-XXS3RN	600mA	SOT23-3L	7-in reel 3000pcs/reel	-40∼85° ℃	RoHS
AS9116-XXS5RN	600mA	SOT23-5L	7-in reel 3000pcs/reel	-40∼85 ℃	RoHS
AS9116-XXDRY	600mA	DFN1010-4L	7-in reel 10000pcs/reel	-40∼125° C	RoHS
AS9116-XXS5RY	600mA	SOT23-5L	7-in reel 3000pcs/reel	-40∼125 ℃	RoHS

• Marking Information & Pin Assignment


DFN1010-4L






Pin Name	Pin No.	I/O	Pin Function	
Fill Malle	DFN1010-4L			
VOUT	1	0	Output Pin	
GND	2	Р	Ground	
EN	3	I	Pull this pin high to enable IC, pull this pin low to shutdown IC.	
VIN	4	Р	Input Power Supply	
EP	-	-	Please Connected to GND.	

SOT23-5L






Pin Name	Pin No.	- I/O	Pin Function	
Fin Name	SOT23-5L			
VIN	1	Р	Input Power Supply	
GND	2	Р	Ground	
EN	3	I	Pull this pin high to enable IC, pull this pin low to shutdown IC.	
NC	4	-	Not Connected.	
VOUT	5	0	Output Pin	



Packing Information



Package Type	Carrier Width(W)	Pitch(P)	Reel Size(D)	Packing Minimum
DFN1010-4L	8.0±0.1 mm	2.0±0.1 mm	180±1 mm	10000pcs
SOT23-5L	8.0±0.1 mm	4.0±0.1 mm	180±1 mm	3000pcs
SOT23-3L	8.0±0.1 mm	4.0±0.1 mm	180±1 mm	3000pcs

Note: Carrier Tape Dimension, Reel Size and Packing Minimum